

Digital B&W Multi Function Printer

MP 1813L

Copier/ Printer/ Scanner

RICOH
imagine. change.



MP 1813L

18 B/W
ppm

MP 1813L

SPECIFICATIONS

GENERAL

Warm-up time: 10 seconds
First output time: 6.5 seconds
Continuous output speed: 18 pages per minute
Memory: Standard: 128 MB
Dimensions (WxDxH): 586.8 × 568 × 430.5 mm
Weight: 37 kg
Power source: 220V-240V, 50/60Hz

COPIER

Copying process: Laser beam scanning and electro photographic printing
Multiple copying: Up to 99 copies
Resolution: 600 dpi
Zoom: From 50 to 200%
Copy features: Series Copy, Combine Copy, Image Rotation, Electronic Sorting, ID Card Copy

PRINTER

Printer language: GDI
Resolution: 600 x 600 dpi
Interface: Standard: USB 2.0
Option: Ethernet 10 base-T / 100 base-TX
Network protocol: TCP/IP (IPv4), IPP
Supported environments: Windows® XP/Vista/7/Server2003/Server 2008/ Server 2008 R2/ Open SUSE (KDE & Gnome): v12.1/ Ubuntu (Gnome): v11.1/ Ubuntu (KDE): v11.1

SCANNER

Scan Type: BW
Scan Mode: Binary/ Halftone/ Grayscale
Resolution: Maximum: 600 dpi
Original size: A3, A4, A5
Bundled drivers: SANE, TWAIN, Network TWAIN (Option)

PAPER HANDLING

Paper input capacity:
Standard: 1 x 250-sheet paper tray, 100-sheet multi-bypass tray
Maximum: 1350 Sheets
Recommended paper size:
Paper tray(s): A5 - A3, Bypass tray: A6 - A3
Paper output capacity: Maximum: 250 sheets
Paper weight: Paper tray(s): 60-90 g/m²
Bypass tray: 60-162 g/m²

ECOLOGY

Power consumption: Maximum: 1,550 W
Ready mode: 113 W
Sleep mode: 0.6 W
TEC (Typical Electricity Consumption): 892/1,082 W/h

OPTIONS

Document Feeder, 1 x 500-sheet paper tray, 2 x 500-sheet paper tray, Network (DDST) option

For availability of models, optional apparatus and software, please consult your Ricoh Representative.

ISO 9001: 2000 certified
ISO 14001 certified

Ricoh has designed these products to meet EC ENERGY STAR guidelines for energy efficiency.

All brand and/or product names are trademarks of their respective owners.

Specifications and external appearance are subject to change without notice. The color of the actual product may vary from the color shown in the brochure.

The images in this brochure are not real photographs and slight differences in detail might appear.

RICOH
imagine. change.

URL: <http://www.ricoh.co.in>

RICOH INDIA LIMITED

CORPORATE OFFICE: 2nd Floor, Salcon Aurum Building, Plot No. 4, District Centre, Jasola, New Delhi-110 025
Tel: (011) 49103000, 49103100, 49103200 Fax: (011) 49103099, 49103199 Email: ril.info@ricoh.co.in SMS: 'RICOH' to 53456
REGISTERED OFFICE: 1201, 1st Floor, Building No. 12, Solitaire Corporate Park, Andheri-Ghatkopar Link Road, Chakala, Andheri-East, Mumbai - 400 093 Tel: (022) 66833000 Fax: (022) 67032099
Ahmedabad, Bangalore, Bhopal, Bhubaneswar, Chandigarh, Chennai, Coimbatore, Delhi, Gurgaon, Guwahati, Hyderabad, Jaipur, Kochi, Kolkata, Lucknow, Mumbai, Nagpur, Patna, Pune, Ranchi, Visakhapatnam.

For more information, please contact: